

## SMD COMMON MODE EMI FILTER / WCB TYPE

### FEATURES

Miniature SMD type common mode filter for fully automated assembly.

Wide impedance range (60Ω~220Ω) for noise suppression.

Excellent Solderability.







### ORDERING CODE

WCB 1608 - 900 Y-N



Note: lead-free  
Tolerance ( Y:±25%)  
Impedance  
Dimension (AxB)  
SMD Common Mode

### DIMENSIONS (UNIT: mm)



A	1.60 ± 0.2	m/m
B	0.80 ± 0.2	m/m
C	1.10 ± 0.2	m/m
D1	0.33 (Ref)	m/m
D2	0.10 (Ref)	m/m

### ELECTRICAL CHARACTERISTICS FOR WCB1608

Part No.	Impedance (Ω)100MHz	DC Resistance (Ω) Max	Rated Current (mA)Max
WCB 1608-600Y-N	60	0.30	300
WCB 1608-670 Y-N	67	0.30	300
WCB 1608-900Y-N	90	0.30	300
WCB 1608-121 Y-N	120	0.36	250
WCB 1608-161Y-N	160	0.40	200
WCB 1608-221Y-N	220	0.42	200



**CORE MASTER ENTERPRISE CO., LTD.**

<http://www.coremaster.com.tw>